

# LED Filament Candle/Round Clear Dimmable & Non-Dimmable






Energy saving LED replacement lamp featuring LED filament technology to closely resemble the look and feel of a traditional incandescent lamp.

- 15,000 hour life
- 7,500 switching cycles
- 2700K warm white
- Colour rendering index Ra≥80
- BC-B22d, ES-E27 cap or SES-E14 cap
- Clear finish
- Dimmable or non-dimmable options
- Dimmable option utilizes DuoDim™ Technology compatible with both leading and trailing edge dimmers\*
- For indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Total Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm) Dia H	Energy Rating	Order Qty
<b>Non-Dimmable Candle - Single Carton</b>										
4436	4	240	BC-B22d	Warm White	2700	470	40	35 91	A++	1
6157	4	240	ES-E27	Warm White	2700	470	40	35 93	A++	1
4443	4	240	SES-E14	Warm White	2700	470	40	35 97	A++	1
<b>Dimmable Candle - Single Carton</b>										
7130	5	240	BC-B22d	Warm White	2700	470	40	35 91	A+	1
7147	5	240	SBC-B15d	Warm White	2700	470	40	35 95	A+	1
7154	5	240	ES-E27	Warm White	2700	470	40	35 93	A+	1
7161	5	240	SES-E14	Warm White	2700	470	40	35 97	A+	1
<b>Non-Dimmable Round - Single Carton</b>										
4450	4	240	BC-B22d	Warm White	2700	470	40	45 76	A++	1
4467	4	240	ES-E27	Warm White	2700	470	40	45 78	A++	1
4474	4	240	SES-E14	Warm White	2700	470	40	45 80	A++	1
<b>Dimmable Round - Single Carton</b>										
7215	5	240	BC-B22d	Warm White	2700	470	40	45 76	A+	1
7222	5	240	SBC-B15d	Warm White	2700	470	40	45 78	A+	1
7239	5	240	ES-E27	Warm White	2700	470	40	45 78	A+	1
7246	5	240	SES-E14	Warm White	2700	470	40	45 80	A+	1

\* The lamp is compatible with most dimmer switches, please refer to website for up-to-date list of compatible dimmer switches.



Experts in lighting since 1878

## LED Filament Candle Dimmable



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-5	Steps 0 - 20%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Steps 0 - 50% Flickers 95 - 100%
Aurora	AU-DSP400X	60W-400W	LED	1-5	Slight flicker at all levels
Danlers	DQDGEU400W	40W-400W	Trailing	1-5	Does not dim below 50%
Danlers	DSS1D 250W	40W-250W	Leading	1-5	Steps 0 - 50%
Danlers	DP1D 400WIET	60W-400W	Leading	1-5	Steps 0 - 20%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps 0 - 20%
MK	K4511xxxLV	40W-220W	Leading	1-5	Dims smooth 0 - 80%
MK	K1521WHILV	40W-300W	Leading	1-5	Flickers 75 - 100%
MK	K1524WHILV	40W-300W	Leading	1-5	Dims smooth 0 - 80%
Zano	ZGRIDLED	5W-250W	LED	1-5	Dims smooth 5 - 100%
Zano	ZANOMO500	11W-50W	Leading	1-5	Dims 0 - 100% Steps 0 - 20%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-5	Dims smooth 0 - 100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-5	Dims smooth 0 - 100%
Eaton	P9131	60W-250W	Leading	1-5	Dims 0 - 80% Steps 0 - 20%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W

*Experts in lighting since 1878*

## LED Filament Round Dimmable



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-5	Steps 0 - 20%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Steps 0 - 20% Flickers 95 - 100%
Aurora	AU-DSP400X	60W-400W	LED	1-5	Slight flicker at all dim levels
Danlers	DQDGEU400W	40W-400W	Trailing	1-5	Does not dim below 50%
Danlers	DSS1D 250W	40W-250W	Leading	1-5	Steps 0 - 50%
Danlers	DP1D 400WIET	60W-400W	Leading	1-5	Steps 0 - 20%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps 0 - 20%
MK	K451 1xxxLV	40W-220W	Leading	1-5	Dims smooth 0 - 80%
MK	K1521 WHILV	40W-300W	Leading	1-5	Flickers 75 - 100%
MK	K1524 WHILV	40W-300W	Leading	1-5	Dims smooth 0 - 80%
Zano	ZGRIDLED	5W-250W	LED	1-5	Dims smooth 5 - 100%
Zano	ZANOMO500	11W-50W	Leading	1-5	Dims 0 - 100% Steps 0 - 20%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-5	Dims smooth 0 - 100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-5	Dims smooth 0 - 100%
Eaton	P9131	60W-250W	Leading	1-5	Dims 0 - 80% Steps 0 - 20%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W

*Experts in lighting since 1878*